

Analogue Multimeter



- Description

This is a high sensitivity pocket size circuit tester equipped with a meter movement of 175 micro amperes sensitivity. Pin-jack range selection system entirely eliminates mechanical switching troubles. The internal batteries measure resistance from 2 ohms upto 1 M ohms. **Range :**

DC voltage :	0.25/10/50/250/1000V (4K ohm/V) $\pm$ 3%
AC voltage :	10/50/250/500/1000V (2K ohm/V) $\pm$ 4%
AC current :	0.25/10/250mA $\pm$ 3%
Resistance :	0-10K/1M ohm (min.2 Ohms & max.1M ohm).
DB :	-20 to + 22, +20 to + 36
Battery :	1.5 V (UM-3) x 2
Capacitance :	0.0001 (100pF) to 0.03 μ F 0.01-0.6 μ F
Inductance :	10 to 1000H